







## **INTRODUCTION**

Aksa power generation system, providing optimum performance, and reliability, for stationary standby, prime power, and continuous duty applications. All generator sets are factory build, and production tested.

Power (kVA) 3 Phase,50 Hz, PF 0.8

Voltage	STANDBY RATING (ESP)		PRIME RATING (PRP)		Standby Amper
Voltage	kW	kVA	kW	kVA	
400/231	52,80	66,00	48,00	60,00	95,27

**STANDBY RATING (ESP)** Applicable for supplying power to varying electrical load for the duration of power interruption of a reliable utility source. ESP is in accordance with ISO 8528-1. Overload is not allowed.

**PRIME RATING (PRP)** Applicable for supplying power to varying electrical load for unlimited hours. PRP is in accordance with ISO 8528-1. 10 % overload capability is available for a period of 1 hour within 12-hour period of operation.

## **General Characteristics**

Model Name	AC 66
Frequency (Hz)	50
Fuel Type	Diesel
Engine Made and Model	CUMMINS S3.8-G7
Alternator Made and Model	ECP 322M/4 C
Control Panel Model	DSE 6120
Canopy	AK 40

## **ENGINE SPECIFICATIONS**

Engine Model S3.8-G7  Number of Cylinder (L) 4 cylinders - in line  Bore (mm.) 97  Stroke (mm.) 128  Displacement (lt.) 3.8  Aspiration Turbo Charged and AfterCooled  Compression Ratio 17.5:1		
Number of Cylinder (L)  Bore (mm.)  Stroke (mm.)  Displacement (It.)  Aspiration  Turbo Charged and AfterCooled  Compression Ratio  4 cylinders - in line  97  128  128  Turbo Charged and AfterCooled  17.5:1	Engine	CUMMINS
Bore (mm.) 97 Stroke (mm.) 128 Displacement (lt.) 3.8 Aspiration Turbo Charged and AfterCooled Compression Ratio 17.5:1	Engine Model	S3.8-G7
Stroke (mm.)  Displacement (lt.)  Aspiration  Compression Ratio  128  3.8  Turbo Charged and AfterCooled  17.5:1	Number of Cylinder (L)	4 cylinders - in line
Displacement (It.)  Aspiration  Turbo Charged and AfterCooled  Compression Ratio  17.5:1	Bore (mm.)	97
Aspiration Turbo Charged and AfterCooled  Compression Ratio 17.5:1	Stroke (mm.)	128
Compression Ratio 17.5:1	Displacement (It.)	3.8
·	Aspiration	Turbo Charged and AfterCooled
RPM (d/dk) 1500	Compression Ratio	17.5:1
Tit W (d/dit)	RPM (d/dk)	1500







Oil Capacity (Total With Filter) (It)	11
Standby Power (kW/HP)	64.9/87
Prime Power	59.6/79.9
Block Heater QTY	1
Block Heater Power (Watt)	750
Fuel Type	Diesel
Injection Type and System	Direct
Type of Fuel Pump	Bosh In-Line
Governor System	Mechanic
Operating Voltage (Vdc)	12 Vdc
Battery and Capacity (Qty/Ah)	1x66
Charge Alternator (A)	40
Cooling Method	Water Cooled
Cooling Fan Air Flow (m3/min)	116
Coolant Capacity (engine only / with radiator) (It)	7/16.5
Air Filter	Dry Type
Fuel Cons. Prime With %100 Load (lt/hr)	14.7
Fuel Cons. Prime With %75 Load (lt/hr)	11
Fuel Cons. Prime With %50 Load (lt/hr)	6.1
ALTERNATOR CHARACTERISTICS	
Manufacturer	Mecc Alte
Alternator Made and Model	ECP 322M/4 C
Frequency (Hz)	50
Power (kVA)	62.5
Voltage (V)	400
Phase	3
A.V.R.	DSR
Voltage Regulation	(+/-)1%
Insulation System	Н
Protection	IP23
Rated Power Factor	0.8
WEIGHT COMP. GENERATOR (Kg)	212
COOLING AIR (m³/min)	15.7
Open Gen.Set Dimensions (mm)	
LENGTH	2150
WIDTH	1050
HEIGHT	1516
DRY WEIGHT (kg.)	1070
TANK CAPACITY (It.)	240





## **Gen.Set Canopy Dimensions (mm)**

LENGTH	3105
WIDTH	1107
HEIGHT	1803
DRY WEIGHT (kg.)	1320
TANK CAPACITY (lt.)	240



- 1. Steel structures
- 2. Emergency stop push button
- 3. Control panel is right side of the set.
- 4. Corrosion resistant locks and hinges
- 5. Sump drains valves
- 6. Sound proof foam metarial
- 7. Lifting Points

### **INTRODUCTION**

Sound–attenuated and Weather-protective Enclosures Sound-attenuated and weather protective enclosures for generating sets from Aksa, meet event the sound requirements and provide optimum protection from inclement weather and development by our specialist acoustic engineers. Our modular designed sound insulated canopies provide ease of access for servicing and general maintenance and interchangeable components permitting on-site repair. Enclosures are designed to optimize genset cooling performance, providing you with confidence that genset ratings and ambient capability.

### **Control Panel**

Control Module	DSE
Control Module Model	DSE 6120
Communication Ports	CANBUS



- 1. Menu navigation buttons
- 2. Close mains button
- 3. Main Status and instrumentation display
- 4. Alarm LED's
- 5. Close generator button
- 6. Status LED's
- 7. Operation selecting buttons

### **Devices**

- -DSE, model 6120 Auto Mains Failure control module.
- -Battery charger input 198-264 volt, output 27,6 V 5 A (24 V) or 13,8 Volt 5A (12V)
- -Emergency stop push button and fuses for control circuits.

### **CONSTRUCTION** and **FINISH**

-Components installed in sheet steel enclosure. Phosphate chemical, pre-coating of steel provides corrosion resistant surface. Polyester composite powder topcoat forms high gloss and extremely durable finish. Lockable and hinged panel door provides easy access to components.

# AC 66





### **INSTALLATION**

Control panel is mounted on baseframe with steel stand. Located at the right side of the generator set (When you look at the Gen.Set. from Alternator)

### **GENERATING SET CONTROL UNIT**

The DSE 6120 module has been designed to monitor generator frequency, volt, current, engine oil pressure, coolant temperature running hours and battery volts.

Module monitors the mains supply and switch over to the generator when the mains power fails.

The DSE6120 also indicates operational status and fault conditions, Automatically shutting down the Gen. Set and giving true first up fault condition of Gen. Set failure. The LCD display indicates the fault.

### STANDARD SPECIFICATIONS

- -Microprocessor controlled.
- -LCD display makes information easy to read.
- -Automatically transfers between mains (utilty) and generator power.
- -Manual programming on front panel.
- -User-friendly set-up and button layout.
- -Remote start.
- -Event logging (50) showing date and time.
- -Controls: Stop/Reset, Manual, Auto, Test, Start, buttons. An additional push button next to the LCD display is used to scroll through the modules' metering displays.

#### Instruments

### **ENGINE**

- -Engine speed.
- -Oil pressure.
- -Coolant temperature.
- -Run time.
- -Battery volts.
- -Configurable timing.

### **GENERATOR**

- -Voltage (L-L, L-N).
- -Current (L1-L2-L3).
- -Frequency.
- -Gen. Set ready.
- -Gen. Set enabled.

#### **MAINS**

- -Mains ready.
- -Mains enabled.

## WARNING

- -Charge failure.
- -Battery Low/High voltage.
- -Fail to stop.

# AC 66





- -Low /High generator voltage.
- -Under /Over generator frequency.
- -Over /Under speed.
- -Low oil pressure.
- -High coolant temperature.

### SHUT DOWNS

- -Fail to start.
- -Emergency stop.
- -Low oil pressure.
- -High coolant temperature.
- -Over /Under speed.
- -Under/over generator frequency.
- -Under/over generator voltage.
- -Oil pressure sensor open.
- -Coolant temperature sensor open.

### **ELECTRICAL TRIP**

-Generator over current.

### **Options**

- -Flexible sensor can be controlled with temperature, pressure, percentage (warning/shutdown/electrical trip)
- -Local setting parameters and monitoring from PC to control module with USB connection (max 6 mt).

## Standards

- -Elecrical Safety / EMC compatibility
- -BS EN 60950 Electrical business equipment.
- -BS EN 61000-6-2 EMC immunity standard.
- -BS EN 61000-6-4 EMC emission standard

## STATIC BATTERY CHARGER

- Battery charger is manufactured with switching-mode and SMD technology and it has high efficiency.
- Battery charger models' output V-I characteristic is very close to square and output is 5 amper, 13,8 V for 12 volt and 27,6 V for 24 V . Input 198 264 volt AC.
- The charger is fitted with a protection diode across the output.
- Connect charge fail relay coil between positive output and CF output.
- They are equipped with RFI filter to reduce electrical noise radiated from the device.
- Galvanically isolated input and output typically 4kV for high reliability.

### STANDARD SPECIFICATIONS

- Water cooled, Diesel engine
- Radiator with mechanical fan
- Protective grille for rotating and hot parts
- Electric starter and charge alternator

# AC 66





- Starting battery (with lead acid) including rack and cables
- Steel base frame and anti-vibration isolators
- Base frame design incorporates an integral fuel tank and anti-vibration isolators
- Flexible fuel connection hoses
- Single bearing, class H alternator
- Industrial exhaust silencer and steel bellows supplied separately
- Static battery charger
- Manual for application and installation

### **OPTIONAL EQUIPMENTS**

### **ENGINE**

Fuel-Water Seperator Filter

Low water level alarm

Oil heater

### **ALTERNATOR**

**Anti-Condensation Heater** 

Over sized alternator

Main line circuit breaker

## **CONTROL SYSTEM**

Remote annunciator panel

Earth fault, single set

Charge Ammeter

### TRANSFER SWITCH

Three or four pole contactor

Three or four pole motor operated circuit breaker

### OTHER ACCESSORIES

Main Fuel Tank

Automatic or manual fuel filling system

Manual oil drain pump

Low and high fuel level alarm

Residential silencer

Enclosure: weater protective or sound attenuated

Duct adapter (on radiator)

Inlet and outlet motorised louvers

Inlet and outlet acoustic baffles

Trailer

Tool kit for maintenance

1500/3000 hours maintenance kit

Double wall chassis

Supplied with oil and coolant - 30 °C

Battery isolating switch







## **AKSA CERTIFICATES**

- TS ISO 8528
- CE
- SZUTEST
- 2000/14/EC