







#### **INTRODUCTION**

Aksa power generation system, providing optimum performance, and reliability, for stationary standby, prime power, and continuous duty applications. All generator sets are factory build, and production tested.

#### Power (kVA) 3 Phase,50 Hz, PF 0.8

Voltage	STANDBY RATING (ESP)		PRIME RATING (PRP)		Standby Amper
Voltage	kW	kVA	kW	kVA	
400/231	360,00	450,00	328,00	410,00	649,54

**STANDBY RATING (ESP)** Applicable for supplying power to varying electrical load for the duration of power interruption of a reliable utility source. ESP is in accordance with ISO 8528-1. Overload is not allowed.

**PRIME RATING (PRP)** Applicable for supplying power to varying electrical load for unlimited hours. PRP is in accordance with ISO 8528-1. 10 % overload capability is available for a period of 1 hour within 12-hour perod of operation.

#### **General Characteristics**

Model Name	AVP 450
Frequency (Hz)	50
Fuel Type	Diesel
Engine Made and Model	VOLVO TAD1344GE
Alternator Made and Model	ECO 40-2S/4 C
Control Panel Model	DSE 7320
Canopy	MS 70

#### **ENGINE SPECIFICATIONS**

Engine	VOLVO
Engine Model	TAD1344GE
Number of Cylinder (L)	6 cylinders - in line
Bore (mm.)	131
Stroke (mm.)	158
Displacement (lt.)	12.78
Aspiration	Turbo Charged and AfterCooled
Compression Ratio	18.1:1
RPM (d/dk)	1500





Oil Capacity (Total With Filter) (It)	36
Standby Power (kW/HP)	399/543
Prime Power	364/495
Block Heater QTY	1
Block Heater Power (Watt)	3000
Fuel Type	Diesel
Injection Type and System	Direct
Type of Fuel Pump	Delphi E3
Governor System	ECM
Operating Voltage (Vdc)	24 Vdc
Battery and Capacity (Qty/Ah)	2x120
Charge Alternator (A)	80
Cooling Method	Water Cooled
Cooling Fan Air Flow (m3/min)	390
Coolant Capacity (engine only / with radiator) (It)	20/44
Air Filter	Dry Type
Fuel Cons. Prime With %100 Load (lt/hr)	82,22
Fuel Cons. Prime With %75 Load (lt/hr)	62.31
Fuel Cons. Prime With %50 Load (lt/hr)	42.4
ALTERNATOR CHARACTERISTICS	
Manufacturer	Mecc Alte
Alternator Made and Model	ECO 40-2S/4 C
Frequency (Hz)	50
Power (kVA)	450
Voltage (V)	400
Phase	3
A.V.R.	DER1
Voltage Regulation	(+/-)0.5%
Insulation System	Н
Protection	IP23
Rated Power Factor	0.8
WEIGHT COMP. GENERATOR (Kg)	1131
COOLING AIR (m³/min)	54
Open Gen.Set Dimensions (mm)	
LENGTH	2949
	4==0
WIDTH	1550
WIDTH HEIGHT	1550 1923








#### **Gen.Set Canopy Dimensions (mm)**

LENGTH	4434	
WIDTH	1606	
HEIGHT	2496	
DRY WEIGHT (kg.)	4240	
TANK CAPACITY (It.)	700	



- 1. Steel structures.
- 2. Emergency stop push button.
- **3.** Control panel is mounted on the baseframe . Located at the right side of the generator set.
- 4. Corrosion-resistant locks and hinges.
- 5. Oil could be drained via valve and a hose
- 6. Exhaust system in the canopy.
- 7. Special large access doors for easy maintanance
- **8.** In front and back side special large access doors for easy maintanance
- 9. Base frame -fuel tank.
- **11.** The cap on the canopy provides easy accsess to radiator cap.
- 12. Sound proofing materials
- 13. Plastic air intake pockets.

#### **INTRODUCTION**

Sound-attenuated and weather protective enclosures for generating sets from Aksa, meet event the sound requirements and provide optimum protection from inclement weather and development by our specialist acoustic engineers. Our modular designed sound insulated canopies provide ease of access for servicing and general maintenance and interchangeable components permitting on-site repair. Enclosures are designed to optimize genset cooling performance, providing you with confidence that genset ratings and ambient capability.

#### **Control Panel**

Control Module	DSE
Control Module Model	DSE 7320
Communication Ports	MODBUS



- 1. Menu navigation buttons
- 2. Close mains button
- 3. Main Status and instrumentation display
- 4. Alarm LED's
- 5. Close generator button
- 6. Status LED's
- 7. Operation selecting buttons

#### **Devices**

DSE, model 7320 Auto Mains Failure control module Static battery charger Emergency stop push button and fuses for control circuits

#### **CONSTRUCTION and FINISH**

Comonents installed in sheet steel enclosure.

Phosphate chemical, pre-coating of steel provides corrosion resistant surface

Polyester composite powder topcoat forms high gloss and extremely durable finish







Lockable hinged panel door provides for easy component access

#### **INSTALLATION**

Control panel is mounted generating set baseframe on robust steel stand or power module. Located at side of generating set with properly panel visibility.

#### **GENERATING SET CONTROL UNIT**

The DSE 7320 conrol module is a standard addition to our generator sets from 220 kVA upwards and it has been designed to start and stop diesel andgas generating sets that include electronic and non electronic engines.

The DSE 7320 includes the additional capability of being able to monitor a mains (utility) supply and is therefore suitable for controlling a standby generating set in conjunction with an automatic transfer switch.

The DSE7320 also indicates operational status and fault conditions, automatically shutting down the generating set and indicating faults by means of its LCD display on the front panel.

#### STANDARD SPECIFICATIONS

Microprocessor controlled

- 132 x 64 pixel LCD display makes information easy to read
- Front panel programming and also via PC software
- Soft touch membrane keypad and five key menu navigation
- Remote communications via RS232, RS485 and ethernet.
- Event logging (50) showing date and time
- Multiple date and time engine exercise mode and maintenance scheduler
- Engine block heater control.
- Controls; stop, manuel, auto, test, start, mute lamb test/transfer to generator, transfer to mains, menu navigation.

#### Instruments

**ENGINE** 

Engine speed

Oil pressure

Coolant temperature

Run time Battery volts

Engine maintenance due

**GENERATOR** 

Voltage (L-L, L-N)

Current (L1-L2-L3)

Frequency

Earth current

kW

Ρf

kVAr

kWh, kVAh, kVArh

Phase sequence

**MAINS** 

Voltage (L-L, L-N)





Frequency

WARNING

Charge failure

Battery under voltage

Fail to stop

Low fuel level (opt.)

kW over load

Negative phase sequence

Loss of speed signal

PRE-ALARMS

Low oil pressure

High engine temperature

Low engine temperature

Over /Under speed

Under/over generator frequency

Under/over generator voltage

ECU warning

SHUT DOWNS

Fail to start

**Emergency stop** 

Low oil pressure

High engine temperature

Low coolant level

Over /Under speed

Under/over generator frequency

Under/over generator voltage

Oil pressure sensor open

Phase rotation

**ELECTRICAL TRIP** 

Earth fault

kW over load

Generator over current

Negative phase sequence

#### **Options**

High oil temperature shut down

Low fuel level shut down

Low fuel level alarm

High fuel level alarm





#### **EXPANSION MODULES**

Editional LED module (2548)

Expension relay module (2157)

Expansion input module (2130)

#### **Standards**

Elecrical Safety / EMC compatibility

BS EN 60950 Electrical business equipment

BS EN 61000-6-2 EMC immunity standard

BS EN 61000-6-4 EMC emission standard

#### STATIC BATTERY CHARGER

Battery charger is manufactured with switching-mode and SMD technology and it has high efficincy.

Battery charger models' output V-I characteristic is very close to square

2405 has fully output shot circuit protection and it can be used as a current source.

2405 charger has high efficiency, long life, low failure rate, light weight and low heat radiated in accordance with linear alternatives.

The charger is fitted with a protection diode across the output.

Charge fail output is available.

Connect charge fail relay coil between positive output and CF output.

Input: 196-264V.

Output: 27,6V 5A or 13,8V 5A.

#### STANDARD SPECIFICATIONS

- Water cooled, Diesel engine
- Radiator with mechanical fan
- Protective grille for rotating and hot parts
- Electric starter and charge alternator
- Starting battery (with lead acid) including rack and cables
- Engine coolant heater
- Base frame design incorporates an integral fuel tank and anti-vibration isolators
- Flexible fuel connection hoses
- Single bearing, class H alternator
- Industrial exhaust silencer and steel bellows supplied separately(for open sets)
- Static battery charger
- Manual for application and installation
- Generators Sets' voltage and frequency regulation comply with ISO 8528-5
- Generators Sets' can take 100% load at one step according to NFPA110

#### **OPTIONAL EQUIPMENTS**

#### **ENGINE**

Fuel-Water Seperator Filter

Oil heater





#### **ALTERNATOR**

**Anti-Condensation Heater** 

Main line circuit breaker

#### **CONTROL SYSTEM**

Automatic synchronising and power control system (multi gen-set Parallel)

Paralel system with mains.

Transition synchronization with mains

Remote relay output

Alarm output relays

Remote communication with modem

Earth fault, single set

Charge Ammeter

#### TRANSFER SWITCH

Three or four pole contactor

Three or four pole motor operated circuit breaker

#### OTHER ACCESSORIES

Main Fuel Tank

Automatic or manual fuel filling system

Electrical oil drain pump

Low and high fuel level alarm

Residential silencer

Enclosure: weater protective or sound attenuated

Duct adapter (on radiator)

Inlet and outlet motorised louvers

Inlet and outlet acoustic baffles

Tool kit for maintenance

1500/3000 hours maintenance kit

Supplied with oil and coolant - 30 °C

#### **AKSA CERTIFICATES**

- TS ISO 8528
- TS ISO 9001-2008
- CE
- SZUTEST
- 2000/14/EC