




## INTRODUCTION

Aksa power generation system, providing optimum performance, and reliability, for stationary standby, prime power, and continuous duty applications. All generator sets are factory build, and production tested.

### Power (kVA)

3 Phase, 60 Hz, PF 0.8

| Voltage | STANDBY RATING (ESP) |         | PRIME RATING (PRP) |        | Standby Amper |
|---------|----------------------|---------|--------------------|--------|---------------|
|         | kW                   | kVA     | kW                 | kVA    |               |
| 380/220 | 720,00               | 900,00  | 656,00             | 820,00 | 1367,45       |
| 480/277 | 816,00               | 1020,00 | 736,00             | 920,00 |               |

**STANDBY RATING (ESP)** Applicable for supplying power to varying electrical load for the duration of power interruption of a reliable utility source. ESP is in accordance with ISO 8528-1. Overload is not allowed.

**PRIME RATING (PRP)** Applicable for supplying power to varying electrical load for unlimited hours. PRP is in accordance with ISO 8528-1. 10 % overload capability is available for a period of 1 hour within 12-hour period of operation.

## General Characteristics

|                           |                        |
|---------------------------|------------------------|
| Model Name                | AC 1020-6              |
| Frequency (Hz)            | 60                     |
| Fuel Type                 | Diesel                 |
| Engine Made and Model     | CUMMINS QSK23-G3 60 Hz |
| Alternator Made and Model | ECO 43-1S/4 A - 60Hz   |
| Control Panel Model       | DSE 7320               |
| Canopy                    | AK 90                  |

## ENGINE SPECIFICATIONS

|                        |                                     |
|------------------------|-------------------------------------|
| Engine                 | CUMMINS                             |
| Engine Model           | QSK23-G3 60 Hz                      |
| Number of Cylinder (L) | 6 cylinders - in line               |
| Bore (mm.)             | 170                                 |
| Stroke (mm.)           | 170                                 |
| Displacement (lt.)     | 23.15                               |
| Aspiration             | Turbo Charged and Charge Air Cooled |



|                                                     |                |
|-----------------------------------------------------|----------------|
| Compression Ratio                                   | 16.0:1         |
| RPM (d/dk)                                          | 1800           |
| Oil Capacity (Total With Filter) (lt)               | 103            |
| Standby Power (kW/HP)                               | 895/1200       |
| Prime Power                                         | 809/1085       |
| Block Heater QTY                                    | 1              |
| Block Heater Power (Watt)                           | 3000           |
| Fuel Type                                           | Diesel         |
| Injection Type and System                           | Direct         |
| Type of Fuel Pump                                   | Cummins HPI-PT |
| Governor System                                     | Electronic     |
| Operating Voltage (Vdc)                             | 24 Vdc         |
| Battery and Capacity (Qty/Ah)                       | 2x143          |
| Charge Alternator (A)                               | 35             |
| Cooling Method                                      | Water Cooled   |
| Cooling Fan Air Flow (m3/min)                       | 625,8          |
| Coolant Capacity (engine only / with radiator) (lt) | 46,5/120       |
| Air Filter                                          | Dry Type       |
| Fuel Cons. Prime With %100 Load (lt/hr)             | 189            |
| Fuel Cons. Prime With %75 Load (lt/hr)              | 139            |
| Fuel Cons. Prime With %50 Load (lt/hr)              | 97             |

#### ALTERNATOR CHARACTERISTICS

|                             |                      |
|-----------------------------|----------------------|
| Manufacturer                | Mecc Alte            |
| Alternator Made and Model   | ECO 43-1S/4 A - 60Hz |
| Frequency (Hz)              | 60                   |
| Power (kVA)                 | 960                  |
| Voltage (V)                 | 480                  |
| Phase                       | 3                    |
| A.V.R.                      | DER1                 |
| Voltage Regulation          | (+/-)0.5%            |
| Insulation System           | H                    |
| Protection                  | IP23                 |
| Rated Power Factor          | 0.8                  |
| WEIGHT COMP. GENERATOR (Kg) | 1870                 |
| COOLING AIR (m³/min)        | 108                  |

#### Open Gen.Set Dimensions (mm)

|        |      |
|--------|------|
| LENGTH | 4121 |
| WIDTH  | 1705 |
| HEIGHT | 2253 |



DRY WEIGHT (kg.) 5950

TANK CAPACITY (lt.) 1500

### Gen.Set Canopy Dimensions (mm)


LENGTH 6500

WIDTH 2200

HEIGHT 2350

DRY WEIGHT (kg.) 9300

TANK CAPACITY (lt.) 1100




1. Steel structure made from steel sheet and steel profiles.
2. canopy and panels made from powder coated sheet steel.
3. Emergency stop push button.
4. Control panel is mounted on the baseframe . Located at the right side of the generator set.
5. Cables out locations are under or back of the canopy.
6. Corrosion.resistant locks and hinges.
7. oil could be drained via valve and a hose
8. Exhaust system in the canopy.
9. special large access doors (marine type) for easy maintenance
10. Fuel tank is at front of the canopy ,easy access to the fuel tank via lockable door.
11. Lifting points similar to ISO container , located on each top corner of the canopy.
12. the cap on the canopy provides easy access to radiator cap.
13. sound proofing materials
14. Integrated ladder built in to side of the canopy allows access to the top of the canopy.

### INTRODUCTION

Sound-attenuated and weather protective enclosures for generating sets from Aksa, meet even the sound requirements and provide optimum protection from inclement weather and development by our specialist acoustic engineers. Our modular designed sound insulated canopies provide ease of access for servicing and general maintenance and interchangeable components permitting on-site repair. Enclosures are designed to optimize genset cooling performance, providing you with confidence that genset ratings and ambient capability.

### Control Panel

|                      |          |
|----------------------|----------|
| Control Module       | DSE      |
| Control Module Model | DSE 7320 |
| Communication Ports  | MODBUS   |



1. Menu navigation buttons
2. Close mains button
3. Main Status and instrumentation display
4. Alarm LED's
5. Close generator button
6. Status LED's
7. Operation selecting buttons

### Devices



DSE, model 7320 Auto Mains Failure control module Static battery charger Emergency stop push button and fuses for control circuits

### CONSTRUCTION and FINISH

Comonents installed in sheet steel enclosure.

Phosphate chemical, pre-coating of steel provides corrosion resistant surface

Polyester composite powder topcoat forms high gloss and extremely durable finish

Lockable hinged panel door provides for easy component access

### INSTALLATION

Control panel is mounted generating set baseframe on robust steel stand or power module. Located at side of generating set with properly panel visibility.

### GENERATING SET CONTROL UNIT

The DSE 7320 control module is a standard addition to our generator sets from 220 kVA upwards and it has been designed to start and stop diesel and gas generating sets that include electronic and non electronic engines.

The DSE 7320 includes the additional capability of being able to monitor a mains (utility) supply and is therefore suitable for controlling a standby generating set in conjunction with an automatic transfer switch.

The DSE7320 also indicates operational status and fault conditions, automatically shutting down the generating set and indicating faults by means of its LCD display on the front panel.

### STANDARD SPECIFICATIONS

Microprocessor controlled

- 132 x 64 pixel LCD display makes information easy to read
- Front panel programming and also via PC software
- Soft touch membrane keypad and five key menu navigation
- Remote communications via RS232, RS485 and ethernet.
- Event logging (50) showing date and time
- Multiple date and time engine exercise mode and maintenance scheduler
- Engine block heater control.
- Controls; stop, manuel, auto, test, start, mute lamb test/transfer to generator, transfer to mains, menu navigation.

### Instruments

#### ENGINE

Engine speed

Oil pressure

Coolant temperature

Run time Battery volts

Engine maintenance due

#### GENERATOR

Voltage (L-L, L-N)

Current (L1-L2-L3)

Frequency

Earth current

kW



Pf

kVAr

kWh, kVAh, kVArh

Phase sequence

MAINS

Voltage (L-L, L-N)

Frequency

WARNING

Charge failure

Battery under voltage

Fail to stop

Low fuel level (opt.)

kW over load

Negative phase sequence

Loss of speed signal

PRE-ALARMS

Low oil pressure

High engine temperature

Low engine temperature

Over /Under speed

Under/over generator frequency

Under/over generator voltage

ECU warning

SHUT DOWNS

Fail to start

Emergency stop

Low oil pressure

High engine temperature

Low coolant level

Over /Under speed

Under/over generator frequency

Under/over generator voltage

Oil pressure sensor open

Phase rotation

ELECTRICAL TRIP

Earth fault

kW over load

Generator over current



Negative phase sequence

#### Options

High oil temperature shut down

Low fuel level shut down

Low fuel level alarm

High fuel level alarm

#### EXPANSION MODULES

Editional LED module (2548)

Expension relay module (2157)

Expansion input module (2130)

#### Standards

Electrical Safety / EMC compatibility

BS EN 60950 Electrical business equipment

BS EN 61000-6-2 EMC immunity standard

BS EN 61000-6-4 EMC emission standard

### STATIC BATTERY CHARGER

Battery charger is manufactured with switching-mode and SMD technology and it has high efficiency.

Battery charger models' output V-I characteristic is very close to square

2405 has fully output shot circuit protection and it can be used as a current source.

2405 charger has high efficiency, long life, low failure rate, light weight and low heat radiated in accordance with linear alternatives.

The charger is fitted with a protection diode across the output.

Charge fail output is available.

Connect charge fail relay coil between positive output and CF output.

Input: 196-264V.

Output: 27,6V 5A or 13,8V 5A.

### STANDARD SPECIFICATIONS

- Water cooled, Diesel engine
- Radiator with mechanical fan
- Protective grille for rotating and hot parts
- Electric starter and charge alternator
- Starting battery (with lead acid) including rack and cables
- Engine coolant heater
- Base frame design incorporates an integral fuel tank and anti-vibration isolators
- Flexible fuel connection hoses
- Single bearing, class H alternator
- Industrial exhaust silencer and steel bellows supplied separately(for open sets)
- Static battery charger
- Manual for application and installation



## OPTIONAL EQUIPMENTS

### TRANSFER SWITCH

- Three or four pole motor operated circuit breaker
- Four Pole Contactor
- Three Pole Contactor

### OTHER ACCESSORIES

- Tool kit for maintenance
- Trailer
- Inlet and outlet acoustic baffles
- Automatic transfer switch
- Main Fuel Tank
- Supplied with oil and coolant - 30 °C
- Inlet and outlet motorised louvers
- Low and high fuel level alarm
- Electrical oil drain pump
- Automatic or manual fuel filling system
- Duct adapter ( on radiator)
- Enclosure: weater protective or sound attenuated
- Residential silencer

### CONTROL SYSTEM

- Remote communication with modem
- Alarm output relays
- Charge Ammeter
- Earth fault, single set
- Remote relay output
- Paralel system with mains.
- Automatic synchronising and power control system ( multi gen-set  
Parallel )
- Remote annunciator panel
- Transition synchronization with mains

### ENGINE

- Oil heater
- Fuel-Water Seperator Filter

### ALTERNATOR

- Main line circuit breaker
- Over sized alternator
- Anti-Condensation Heater

## AKSA CERTIFICATES



- TS ISO 8528
- CE
- SZUTEST
- 2000/14/EC